

# Tension link

## With thin-film technology from 5 kN

### Models F7301, F73C1, F73S1

WIKA data sheet FO 51.19



#### Applications

- Crawler cranes, mobile cranes, harbour cranes, for recording load and torque
- Conveyor systems
- Drives and winches
- Cable winch measurement
- Ship-lifting facilities


#### Special features

- Measurement ranges from 0 ... 5 kN
- Fine-grained structural steel with high-quality surface protection or in corrosion-resistant stainless steel version
- High long-term stability, high shock and vibration resistance, excellent reproducibility
- For dynamic and static measurements
- Option: Redundant output signals

#### Description

Tension links are designed for static and dynamic measurement tasks in the direct flux of force. As a load-bearing component in existing constructions, they determine the tension forces in a wide scope of applications.

Tension links of this series are often used in hoist and crane systems as torque support or rope fix point for load measurements. Further application areas are special machine constructions, e. g. in polymer processing machines. Appropriate technical and regional approvals are available as an option.



**Tension links, Model F7301, F73C1, F73S1**

The tension links of the series F7301 are either made of high-strength, corrosion-resistant stainless steel 1.4542 or robust fine-grained steel with surface protection. Due to their properties, these materials are particularly suitable for the applications of tension links.

Besides the standard active current and voltage outputs (4 ... 20 mA / 0 ... 10 V), digital outputs (CANopen®) are available as output signals.

Redundant output signals are possible.

These force transducers are a part of our certified product ELMS1 overload protection (DIN EN ISO 13849-1 with PL d/ Kat. 3 and SIL 2).

# Technical data in accordance with VDI/VDE/DKD 2638

| Models   | F7301   | F73S1   |
|--|---|---|
| Rated force $F_{nom}$ kN   | from 5  |   |
| Relative linearity error $d_{lin}$ <sup>1)</sup>                                     | $\pm 0.5 \% F_{nom}$  |   |
| Relative repeatability error in unchanged mounting position $b_{rg}$                 | $\pm 0.05 \% F_{nom}$   |   |
| Temperature effect on<br>■ characteristic value $TK_c$<br>■ zero signal $TK_0$       | 0.2 % $F_{nom}/10$ K<br>0.2 % $F_{nom}/10$ K  |   |
| Force limit $F_L$  | 150 % $F_{nom}$   |   |
| Breaking force $F_B$   | 300 % $F_{nom}$   |   |
| Shear force influence $d_Q$<br>(Signal with 100 % $F_{nom}$ under 90°) <sup>2)</sup> | $\pm 2 \% F_{nom}$  |   |
| Rated displacement (typ.) $s_{nom}$  | < 0.1 mm  |   |
| Material of measuring device   | corrosion resistant stainless steel or fine-grained steel with surface protection, ultrasonic tested 3.1 material (optionally 3.2)  |   |
| Rated temperature $B_{T, nom}$   | -20 ... +80 °C  |   |
| Operating temperature $B_{T, G}$   | -30 ... +80 °C (optional -40...+80 °C)  | -30 ... +80 °C  |
| Storage temperature $B_{T, S}$   | -40 ... +85 °C  |   |
| Electrical connection  | Circular connector M 12x1, 4-pin<br>CANopen® 5-pin<br>MIL connector   | 2-circular connector M 12x1, 4-pin<br>MIL connector   |
| Output signal<br>(rated output) $C_{nom}$  | 4 ... 20 mA, 2-wire,<br>4 ... 20 mA, 3-wire<br>2 x 4 ... 20 mA, redundant<br>DC 0 ... 10 V, 3-wire<br>2 x DC 0 ... 10 V redundant<br>CANopen® Protocol in accordance with<br>CiA 301, device profile 404, communication<br>services LSS (CiA 305), configuration of the<br>instrument address and baud rate Sync/Async,<br>Node/Lifeguarding, heartbeat; zero and span<br>$\pm 10 \%$ adjustable via entries in the object<br>directory <sup>3)</sup> | Redundant opposing<br>4 ... 20 mA/ 20 ... 4 mA acc. to the<br>requirements for functional safety<br>Machinery Directive 2006/42/EG                      |
| Current consumption  | Current output 4 ... 20 mA 2-wire: signal current<br>Current output 4 ... 20 mA, 3-wire: < 8 mA<br>Voltage output: < 8 mA<br>CANopen®: < 1 W  | Current output 4 ... 20 mA: signal current  |
| Supply voltage   | DC 10 ... 30 V for current output<br>DC 14 ... 30 V for voltage output<br>DC 12 ... 30 V for CANopen®   | DC 10 ... 30 V for current output   |
| Burden   | $\leq (UB-10 \text{ V})/0.024 \text{ A}$ for current output<br>> 10 k $\Omega$ for voltage output   | $\leq (UB-10 \text{ V})/0.020 \text{ A}$ (channel 1)<br>for current output<br>$\leq (UB-7 \text{ V})/0.020 \text{ A}$ (channel 2)<br>for current output |
| Response time  | $\leq 2 \text{ ms}$ (within 10 ... 90 % $F_{nom}$ ) <sup>4)</sup>   |   |
| Protection (acc. to EN/IEC 60529)  | IP67 (optional IP69k)   | IP67  |
| Electrical protection  | Reverse voltage, overvoltage and short-circuit protection   |   |
| Vibration resistance   | 20 g, 100 h, 50...150 Hz (acc. to DIN EN 60068-2-6)   |   |
| Noise emission   | DIN EN 55011  |   |
| Noise immunity   | In accordance with DIN EN 61326-1/DIN EN 61326-2-3 (optional EMC-strengthened versions)   |   |
| Optional   | Certificates, strength verifications, 3D-CAD files (STEP, IGES) on request  |   |

1) Relative linearity error acc. to VDI/VDE/DKD 2638 chap. 3.2.6.

2) This value can be reached when 100 %  $F_{nom}$  act. 90° rotated to the axis.

3) Protocol acc. to CiA DS-301 V.402. Device profile DS-404 V. 1.2.

4) Other response times are available on request.

CANopen® and CiA® are registered community trade marks of CAN in Automation e.V.

| Models  | F73C1<br>ATEX/IECEX EX ib <sup>1)</sup>   | F73C1<br>signal jump   |
|---|---|--|
| Rated force $F_{nom}$ kN  | from 5  |  |
| Relative linearity error $d_{lin}$ <sup>2)</sup>                                    | $\pm 0.5 \% F_{nom}$  |  |
| Relative repeatability error in unchanged mounting position $b_{rg}$                | $\pm 0.05 \% F_{nom}$   |  |
| Temperature effect on<br>■ characteristic value $TK_c$<br>■ zero signal $TK_0$      | 0.2 % $F_{nom}/10$ K<br>0.2 % $F_{nom}/10$ K  |  |
| Force limit $F_L$   | 150 % $F_{nom}$   |  |
| Breaking force $F_B$  | 300 % $F_{nom}$   |  |
| Shear force influence $d_Q$<br>(Signal with 100% $F_{nom}$ under 90°) <sup>3)</sup> | $\pm 2 \% F_{nom}$  |  |
| Rated displacement (typ.) $s_{nom}$   | < 0.1 mm  |  |
| Material of measuring device  | Corrosion resistant stainless steel or fine-grained steel with surface protection, ultrasonic tested 3.1 material / (optionally 3.2)  |  |
| Rated temperature $B_{T, nom}$  | -20 ... +80 °C  |  |
| Operating temperature $B_{T, G}$  | Ex II 2G Ex ib IIC T4 Gb -25 °C < Tamb < +85 °C<br>Ex II 2G Ex ib IIC T3 Gb -25 °C < Tamb < +100 °C<br>Ex I M2 Ex ib I Mb -25 °C < Tamb < +85 °C<br>Ex II 2G Ex ib IIC T4 Gb -40 °C < Tamb < +85 °C<br>Ex I M2 Ex ib I Mb (for cable connection only) | -30 ... +80 °C   |
| Storage temperature $B_{T, S}$  | -40 ... +85 °C  |  |
| Electrical connection   | Circular connector M 12x1, 4-pin<br>MIL connector<br>Cable gland  | Circular connector M 12x1, 4-pin<br>Cable gland  |
| Output signal<br>(rated output) $C_{nom}$   | 4 ... 20 mA, 2-wire   | 4 ... 16 mA, 2-wire <sup>4)</sup><br>DC 2 ... 8 V, 3-wire <sup>4)</sup>  |
| Current consumption   | Current output 4 ... 20 mA<br>2-wire: signal current  | Current output 4 ... 20 mA<br>2-wire: signal current,<br>Current output 4 ... 20 mA<br>3-wire: < 8 mA,<br>Voltage output: < 8 mA |
| Supply voltage  | DC 10 ... 30 V for current output   | DC 10 ... 30 V for current output<br>DC 14 ... 30 V for voltage output   |
| Burden  | < (UB-10 V)/0,024 A for current output<br>> 10 kΩ for voltage output  |  |
| Response time   | $\leq 2$ ms (within 10 ... 90 % $F_{nom}$ ) <sup>5)</sup>   |  |
| Protection (acc. to EN/IEC 60529)   | IP67  |  |
| Electrical protection   | Reverse voltage, overvoltage and short-circuit protection   |  |
| Vibration resistance  | 20 g, 100 h, 50...150 Hz acc. to DIN EN 60068-2-6   |  |
| Noise emission  | DIN EN 55011  |  |
| Noise immunity  | In accordance with DIN EN 61326-1/DIN EN 61326-2-3 (optional EMC-strengthened versions)   |  |
| Optional  | Certificates, strength verifications, 3D-CAD files (STEP, IGES) on request  |  |
| Certificates (optional)   | <b>ATEX:</b> acc. to EN 60079-0:2012 and EN 60079-11:2012 (Ex ib)<br><b>IECEX:</b> acc. to IEC 60079-0:2011 (Ed.6) and IEC 60079-11:2011 (Ed. 6) (Ex ib)<br><b>UL:</b> acc. to UL 61010-1 and CSA C22.2 NO. 61010-1                                   |  |

1) The tension links with ignition protection type "ib" must only be supplied using galvanically-isolated power supplies.


2) Relative linearity error acc. to VDI/VDE/DKD 2638 chap. 3.2.6.

3) This value can be reached when 100 %  $F_{nom}$  act. 90° rotated to the axis.

4) Other signal jumps are available on request.



5) Other response times are available on request.

Mounting situation of the tension link



Dimensions: The customer-specific transducer drawing for the specific article number applies above all.  
For the F7301, F73C1, F73S1 series, there are no standard dimensions. All dimensions in mm.

Pin assignment analogue output



| Circular connector M12 x 1, 4-pin |                       |                       |                      |
|-----------------------------------|-----------------------|-----------------------|----------------------|
|                                   | 4 ... 20 mA<br>2-wire | 4 ... 20 mA<br>3-wire | 0 ... 10 V<br>3-wire |
| Supply UB+                        | 1                     | 1                     | 1                    |
| Supply 0V/UB-                     | 3                     | 3                     | 3                    |
| Signal S+                         | 1                     | 4                     | 4                    |
| Signal S-                         | 3                     | 3                     | 3                    |
| Screen ⊕                          | Case                  | Case                  | Case                 |

| Cable outlet |        |        |
|--------------|--------|--------|
| Cable colour | 2-wire | 3-wire |
| Brown        | UB+/S+ | UB+    |
| White        | -      | -      |
| Blue         | 0V/S-  | 0V/S-  |
| Black        | -      | S+     |

Only when using the standard cable, e.g. EZE53X011016

Pin assignment ATEX/IECEX

| Circular connector M12 x 1, 4-pin |                                   |
|-----------------------------------|-----------------------------------|
|                                   | ATEX Ex ib<br>4...20 mA<br>2-wire |
| Supply UB+                        | 1                                 |
| Supply 0V/UB-                     | 3                                 |
| Signal S+                         | 1                                 |
| Signal S-                         | 3                                 |
| Screen⊕                           | Case                              |

| Cable outlet |        |
|--------------|--------|
| Cable colour | 2-wire |
| Brown        | UB+/S+ |
| White        | -      |
| Blue         | 0V/S-  |
| Black        | -      |

Only when using the standard cable, e.g. EZE53X011016

## Pin assignment signal jump


| Circular connector M12 x 1, 4-pin |                     |                     |                    |
|-----------------------------------|---------------------|---------------------|--------------------|
|                                   | 4...20 mA<br>2-wire | 4...20 mA<br>3-wire | 0...10 V<br>3-wire |
| Supply UB+                        | 1                   | 1                   | 1                  |
| Supply 0V/UB-                     | 3                   | 3                   | 3                  |
| Relay UR+                         | 2                   | 2                   | 2                  |
| Relay UR-                         | 4                   | 3                   | 3                  |
| Signal S+                         | 1                   | 4                   | 4                  |
| Signal S-                         | 3                   | 3                   | 3                  |
| Screen ⊕                          | Case                | Case                | Case               |

| Cable outlet |        |           |
|--------------|--------|-----------|
| Cable colour | 2-wire | 3-wire    |
| Brown        | UB+/S+ | UB+       |
| White        | UR+    | UR+       |
| Blue         | 0V/S-  | 0V/S-/UR- |
| Black        | UR-    | S+        |

Only when using the standard cable, e.g. EZE53X011016

## Pin assignment, analogue output, redundant, opposing

| Circular connector M12 x 1, 4-pin |  |             |
|-----------------------------------|--|-------------|
|                                   | 4 ... 20 mA / 20 ... 4 mA<br>(redundant) |             |
|                                   | Connector 1                              | Connector 2 |
| Supply UB+                        | 1  | 1           |
| Supply 0V/UB-                     | 3  | 3           |
| Signal channel 1                  | 4  | -           |
| Signal channel 2                  | -  | 4           |
| Screen ⊕                          | Case                                     | Case        |



Circular connector  
M12 x 1, 4-pin

2-connector variant, for example, in combination with ELMS1 overload protection (F73S1).

Version in accordance with requirements for functional safety per 2006/42/EC Machinery Directive.

## Pin assignment, analogue output with MIL connector

| MIL      | mA/V 3-wire |           | mA/V 2-wire |           |
|----------|-------------|-----------|-------------|-----------|
| A        | UB+         | Channel 1 | UB+ / S+    | Channel 1 |
| C        | 0V / S-     |           | 0V / S-     |           |
| D        | S+          |           | UB+ / S+    | Channel 2 |
| B        | UB+         | Channel 2 | -           |           |
| E        | 0V / S-     |           | -           |           |
| F        | S+          |           | 0V / S-     | Channel 2 |
| G        | -           |           | -           | -         |
| Screen ⊕ | Case        |           | Case        | -         |



MIL-CA3102E 16S-1P-B

## Pin assignment CANopen®

| Circular connector M12 x 1, 5-pin |   |
|-----------------------------------|---|
| Screen ⊕                          | 1 |
| Supply UB+ (CAN V+)               | 2 |
| Supply UB- (CAN GND)              | 3 |
| Bus-Signal CAN-High               | 4 |
| Bus-Signal CAN-Low                | 5 |




Circular connector  
M12 x 1, 5-pin

Connect the cable shield to the force transducer housing. In the case of accessory cables, the cable shield must be connected with the knurled nut and thus connected to the housing of the force transducer. When extending, only shielded and low capacitance cables should be used. The permitted maximum and minimum lengths of the cable are specified in ISO 11898-2. A high-quality connection of the shielding must also be ensured.

## Short description of signal jump electronics

Amplifier electronics 4 ... 20 mA or 0 ... 10 V for signal jump applications with 2-channel PC control



These force transducers are working with four variable resistors (R1 ... R4) connected to a Wheatstone Bridge. Caused by deformation of the body the respective opposite resistors are lengthened or compressed in the same way. This results in an unbalanced bridge and a diagonal voltage  $U_0$ .

This well proven design has been amended by an additional resistor R7 in order to monitor the condition of the amplifier unit and signal path. This resistor is connected as a shunt to resistor R5 by a relay contact (a) as soon as an excitation voltage  $U_r$  appears at relay A. The connection of resistor R7 will always result in a defined unbalancing of the zero point (diagonal voltage) of the Wheatstone Bridge.


### Compliance with functional safety

An external safety controller independently of the force transducer must monitor the safe functioning of the force transducer. The function test with a signal jump of 4 mA / 2 V is generated at a 24-hour interval. The safety controller activates relay A and thus defines the output signal of the force transducer.

If the expected change in the output signal occurs, it can be assumed that the entire signal path of the Wheatstone bridge via the amplifier to the output functions correctly.

If it does not occur, an error in this signal path can be concluded. Furthermore, the measuring signal is to be checked by the safety controller for the Min- (A) and Max- (B) signal values in order to detect a possibly arising line break or short circuit.

The standard adjustment of force transducers with current output 4 ... 20 mA for overload control is e.g.:



With a fixed signal level of, for example, 4 mA, the testing cycle can be triggered in every operating status upon activation of the check relays. The measurement's upper limit

of 20 mA will not be reached. This enables a check of the signal level.

© 08/2016 WIKA Alexander Wiegand SE & Co. KG, all rights reserved.  
The specifications given in this document represent the state of engineering at the time of publishing.  
We reserve the right to make modifications to the specifications and materials.

