

Izbirni seznam pretvornikov INOR

	BASIC				UNIVERSAL		SMART	
	APAQ C130TC APAQ R130TC	APAQ C130RTD APAQ R130RTD	APAQ-3HPT APAQ-3LPT	IPAQ C202	IPAQ C330 IPAQ R330	IPAQ R460	IPAQ C530 IPAQ R530	IPAQ C520 IPAQ R520
								
Stran	22/30	23/31	38/39	25/32	27/34	40	29/36	29/37
Izvedba								
Montaža v priključno glavo	✓	✓	✓	✓	✓	-	✓	✓
Montaža v priključno glavo, Ex	-	-	-	✓	✓	-	✓	✓
Montaža na DIN letev	✓	✓	✓	✓	✓	✓	✓	✓
Montaža na DIN letev, EX	-	-	-	✓	✓	-	✓	✓
SIL2	-	-	-	-	-	-	-	✓
Vhod								
Uporovno tipalo	2-žično	2-, 3- ali 4-žični	3-žični	3-žični	2-, 3- ali 4-žični			
Termoelement	B, E, J, K, N, R, S, T	-	-	-	B,C,E,J,K,L,N,R,S,T	B,C,E,J,K,L,N,R,S,T	B,C,D,E,J,K,N,R,S,T	B,C,D,E,J,K,N,R,S,T
Ostalo	-	-	-	-	mV, Ω	mV, Ω, KTY	mV, Ω	mV, Ω
Vhodni kanal								
1 Merilni kanal	✓	✓	✓	✓	✓	✓	✓	✓
2 Merilna kanala	-	-	-	-	-	-	-	✓
2 Vhoda	-	-	-	-	-	-	-	✓
Izhodni signal								
4-20 mA	✓	✓	-	✓	✓	✓	✓	✓
0-10 V	-	-	✓	-	-	✓	-	-
HART®	-	-	-	-	-	-	✓	✓
Točnost								
Klasa točnosti	Poglejte tehnični list	±0.15%	±0.15%	±0.1%	±0.08%	±0.1%	±0.08%	±0.05%
Izvedba vezja								
Galvanska izolacija	-	-	-	-	1500 VAC	3000 VAC	1500 VAC	1500 VAC
Napajanje								
24 V DC	✓	✓	✓	✓	✓	✓	✓	✓
230 V AC	-	-	-	-	-	-	-	-
Konfiguracija								
Consoft (USB)	-	-	✓	✓	✓	-	✓	✓
HART®	-	-	-	-	✓	-	✓	✓
NFC™	✓	✓	-	-	✓	-	✓	-
Bluetooth®	-	-	-	-	✓	✓	✓	-

Izbirni seznam pretvornikov INOR

Dodatki							
Zančno napajanje LED in LCD zaslona, zančno napajanje izolatorja in repetitorjev, pribor za konfiguracijo pretvornika	✓	✓	✓	✓	✓	-	✓
Aplikacija INOR-Connect	✓	✓	-	-	✓	-	✓